

SYSTEM AND METHOD FOR HOST BASED TARGET DEVICE MASKING  
BASED ON UNIQUE HARDWARE ADDRESSES

Inventors:

Ahmad Tawil  
1503 Laurel Oak Loop  
Round Rock, TX 78664

Jacob Cherian  
12345 Lamplight Village Ave., Apt. 1524  
Austin, TX 78758

Assignee:

DELL PRODUCTS, L.P.  
One Dell Way  
Round Rock, Texas 78682-2244

BAKER BOTTS L.L.P.  
One Shell Plaza  
910 Louisiana  
Houston, Texas 77002-4995

Attorney's Docket:

016295.0635  
(DC-02668)

SYSTEM AND METHOD FOR HOST BASED TARGET DEVICE MASKING BASED  
ON UNIQUE HARDWARE ADDRESSES

5

TECHNICAL FIELD

The present disclosure relates in general to the field of computer networks and, more  
particularly, to a system and method for masking devices in a network environment.

10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2

## BACKGROUND

Computer networking environments such as Local Area Networks (LANs) and Wide Area Networks (WANs) permit many users, often at remote locations, to share communication, data, and resources. This combination of a LAN or WAN with a SAN may be referred to as a shared storage network. A SAN may be used to provide centralized data sharing, data backup, and storage management in these networked computer environments. A storage area network is a high-speed subnetwork of shared storage devices. A storage device is any device that principally contains a single disk or multiple disks for storing data for a computer system or computer network. The collection of storage devices is sometimes referred to as a storage pool. The storage devices in a SAN can be collocated, which allows for easier maintenance and easier expandability of the storage pool. The network architecture of most SANs is such that all of the storage devices in the storage pool are available to all the servers on the LAN or WAN that is coupled to the SAN. Additional storage devices can be easily added to the storage pool, and these new storage devices will also be accessible from any server in the larger network.

In a computer network that includes a SAN, the server can act as a pathway or transfer agent between the end user and the stored data. Because much of the stored data of the computer network resides in the SAN, rather than in the servers of the network, the processing power of the servers can be used for applications. Network servers can access a SAN using the Fibre Channel protocol, taking advantage of the ability of a Fibre Channel fabric to serve as a common physical layer for the transport of multiple upper layer protocols, such as SCSI, TCP/IP, and HiPPI, among other examples. As a result, Fibre Channel technology allows data and network protocols to exist on the same physical media. A SAN is created by a system of interconnected host bus adapters (HBAs), Fibre Channel bridges, storage devices and Fibre Channel switches. A Fibre Channel fabric is created by a system of interconnected Fibre Channel switches. A SAN may contain multiple fabrics for redundancy and improve fault tolerance. A Fibre Channel bridge allows SCSI devices to be connected to the Fibre Channel fabric. A Fibre Channel switch handles multiple connections between storage devices and servers. A HBA is a PCI adapter card that resides in a server and functions to convert data commands from a PCI-bus format to a storage interconnect format,

such as SCSI or Fibre Channel, and communicate directly with disk drives, tape drives, CD-ROMs, or other storage devices. A HBA controller is a PCI adapter card that performs the same function as a HBA but also has a RAID functionality when communicating with multiple disk drives.

5 In Fibre Channel networks, each device connected to the network is called a node. A node may be a computer, storage device, storage subsystem or any other addressable entity connected to an I/O bus or network. The component of a node that connects the device to the network or bus is called a port. In a network running SCSI protocol, a node can be either an initiator, such as a workstation or server, or a target, such as a data storage device.  
10 In a network that is running a protocol other than SCSI, the nodes are designated as originators and responders, respectively. Fibre Channel supports several network topologies, including point-to-point, switched fabric, arbitrated loop, and combinations thereof.

The storage devices in a SAN may be structured in a RAID configuration. When a system administrator configures a shared data storage pool into a SAN, each storage  
15 device may be grouped together into one or more RAID volumes and each volume is assigned a SCSI logical unit number (LUN) address. If the storage devices are not grouped into RAID volumes, each storage device will typically be assigned its own LUN. The system administrator or the operating system for the network will assign a volume or storage device and its corresponding LUN to each server of the computer network. Each server will then  
20 have, from a memory management standpoint, logical ownership of a particular LUN and will store the data generated from that server in the volume or storage device corresponding to the LUN owned by the server.

When a server is initialized, the operating system assigns all visible storage devices to the server. For example, if a particular server detects several LUNs upon  
25 initialization, the operating system of that server will assume that each LUN is available for use by the server. Thus, if multiple servers are attached to a shared data storage pool, each server can detect each LUN on the entire shared storage pool and will assume that it owns for storage purposes each LUN and the associated volume or storage device. Each server can then store the user data associated with that server in any volume or storage device in the  
30 shared data storage pool. Difficulties occur, however, when two or more servers attempt to

write to the same LUN at the same time. If two or more servers access the same LUN at the same time, the data stored in the volume or storage device associated with that LUN will be corrupted. The disk drivers and file system drivers of each server write a data storage signature on the storage device accessed by the server to record information about how data is stored on the storage system. A server must be able to read this signature in order to access the previously written data on the storage device. If multiple servers attempt to write signatures to the same storage device, the data storage signatures will conflict with each other. As a result, none of the servers will be able to access the data stored in the storage device because the storage device no longer has a valid data storage signature. The data on the storage device is now corrupted and unusable.

To avoid the problem of data corruption that results from access conflicts, conventional storage consolidation software employs LUN masking software. LUN masking software runs on each server and masks the LUNs in order to prevent the operating system from automatically assigning the LUNs. In effect, LUN masking software masks or hides a device from a server. The system administrator may then use the storage consolidation software to assign LUNs to each server as needed. Because a server can access only those devices that it sees on the network, no access conflicts can arise if each LUN is masked to all but one server. In addition to the risk of data corruption, the inherent limitations of a storage device in terms of storage capacity and performance bottlenecks are other reasons for preventing all hosts from having access to the same storage device.

Deployment of large SANs are currently restricted due to the fact that storage devices have limited resources for supporting a large number of hosts on the same SAN. For example, one of the limitations of a storage device is the number of HBAs that can perform port logins per target port on the storage device. Figure 1 is a flow chart of a conventional HBA port login process at device discovery time. Initially, at step 10, the HBA driver queries the Fabric for available target devices, such as storage devices, from the Name Server in the Fabric. Each host in a switched non-zoned SAN sees the same storage device on each of its HBAs. Fabric protocol requires each HBA initiator to issue a port login (PLOGI) to each storage device at initialization time before any I/Os can occur between the HBA and the storage device. Thus, each HBA will issue a port login to each storage device it sees on the

SAN. Because each HBA can see every device on the switched non-zoned SAN, each HBA will issue a port login to every storage device. Accordingly, at step 12, each HBA driver performs a port login with every target device in the Name Server. Next, at step 14, the upper driver, such as the SCSI driver, discovers all target devices with which the HBA driver  
5 logged-in. The HBA driver communicates to the upper driver all the devices it sees on the SAN. Afterward, the server continues with other boot-time procedures, such as LUN masking.

Because a storage device can only support a limited number of port logins, the port login process reduces the number of hosts that a SAN can support. For example, when a  
10 storage device can handle up to thirty-two maximum port logins, then the number of HBAs connected on the SAN cannot exceed thirty-two. Accordingly, no more than thirty-two hosts with single HBAs, or sixteen hosts with dual HBAs can be connected to the same SAN. The SAN environment 16 shown in Figure 2 comprises four hosts 18, each with dual HBAs 20, connected to Fabric 22 consisting of switches 24. Two storage devices 26, with dual  
15 redundant controllers 26 are also coupled to the Fabric 22. In this example, each storage device 26 has a total of eight HBAs logged in with the storage device 26. This SAN environment 16 cannot fully support any additional hosts 18 if the storage devices 26 can only handle a maximum of eight port logins. For instance, if one of the storage devices 26a supported only four HBAs, then only half of the hosts 18 would be able to see that storage  
20 device 26a. Depending on the implementation of the storage device 26a, the rest of the servers 18 will either not see the storage device 26a or they will cause the servers 18 that are already logged in to the storage device 26a to be logged out by the storage device 26a.

A solution to conserve the port login resources of a storage device cannot be based on LUN masking, because the LUN masking process occurs after the HBA port login  
25 process. Currently, system administrators may attempt alleviate this problem by arranging the devices connected to the fabric into one or more logical groups called zones. Switch zoning may be based on World Wide Names or physical ports. Devices in the same zone can see each other but devices in different zones cannot see each other. Zones help to partition the SAN by establishing barriers between different operating system environments and  
30 creating logical fabric subsets. This type of zoning enables resource partitioning for the



SUMMARY

In accordance with teachings of the present disclosure, a system and method for host based device masking based on unique hardware addresses in a network environment are disclosed that provide significant advantages over prior developed systems.

5           The system and method described herein provides for a management application to configure a HBA driver to perform a port login with a target device based on whether the unique hardware address of the target device is included on the HBA driver's unique hardware address access table. During the storage assignment step of the login process, the user selects the target devices that will be assigned to the host. The unique  
10 hardware address of these target devices will be stored on a unique hardware address access table. During the device discovery step of the login process, the HBA driver compares the unique hardware address of the target device with a unique hardware address access table. If the target device's unique hardware address is listed on the unique hardware address access table, then the HBA driver will proceed with a port login with that target device. If the target  
15 device's unique hardware address is not present on the unique hardware address access table, then the HBA driver will forego a port login with that target device. As a result, the HBA driver will not perform a port login with a target device unless that device has been assigned to the host.

20           The disclosed system and method provide several technical advantages over conventional approaches to the HBA port login process in a network environment. One advantage provided by the disclosed system and method is that the HBA driver performs a port login with a selected number of target devices, rather than all of the target devices on the network. As a result, unnecessary HBA port logins to the target devices are substantially eliminated. Accordingly, the number of hosts that may be added to the computer network is  
25 not limited by the number of port logins that a given target device can handle. The disclosed system and method is also advantageous in that it does not divide the network into zones. Other technical advantages should be apparent to one of ordinary skill in the art in view of the specification, claims, and drawings.



BRIEF DESCRIPTION OF THE DRAWINGS

A more complete understanding of the present embodiments and advantages thereof may be acquired by referring to the following description taken in conjunction with the accompanying drawings, in which like reference numbers indicate like features, and  
5 wherein:

Figure 1 is a flow chart of a conventional HBA port login process at device discovery time;

Figure 2 is a diagram illustrating a storage area network;

Figure 3 is a diagram illustrating one embodiment of the present invention;

10 Figure 4 is a flow chart illustrating one embodiment of the HBA port login process during storage assignment of the present invention; and

Figure 5 is a flow chart illustrating one embodiment of the HBA port login process during device discovery of the present invention.

DETAILED DESCRIPTION

Figure 3 is a diagram of a storage area network (SAN), indicated generally at 28. Computer network 28 includes a server network 30. Server network 30 comprises a plurality of hosts or servers 32, which can include UNIX-based servers, WINDOWS NT-based servers, NETWARE servers, thin server computers, and other server or computer systems. Server network 30 may be, for example, a local area network (LAN), a wide area network (WAN), or other network allowing transmission of data between computing devices. Hosts 32 may employ a variety of network protocols for the transfer of data, including TCP/IP. The number of hosts 32 may vary from the number shown in Figure 3 and described in this disclosure. Each host 32 is communicatively coupled to a host bus adapter (HBA) 34. HBA 34 may be a PCI adapter card that resides in host 32 and is operable to convert data commands from a PCI-bus format to a storage interconnect format, such as SCSI or Fibre Channel for example, and thereby communicate directly with storage devices such as disk drives, tape drives and CD-ROMs. HBA 34 may also be a host-based RAID controller. A host-based RAID controller is a PCI adapter card that has the same function as an HBA, but is also operable to perform a RAID functionality when communicating with multiple disk drives. HBA 34 may be a dual HBA to provide redundant functionality. Hosts 32 are loaded with HBA drivers. The HBA driver allows the host 32 to use the HBA card 34 and connect to SAN network 28. The HBA 34 provides an interface between the PCI bus of the server and the storage devices of the SAN 28.

SAN 28 further includes a fabric or switching fabric 36. Fabric 36 may be a high speed network interconnect or high speed optical network interconnect. For example, fabric 36 may be a Fibre Channel fabric. The SAN 28 is created by a set of interconnected HBAs 34, bridges, network devices and switches. The fabric 36 is composed of several switches 38 that allow various electronic interconnections between the various devices that compose computer network 28. For example, in a Fibre Channel fabric, switches 38 will be Fibre Channel switches. Storage subsystem 40 comprises a plurality of physical storage devices 42. Storage devices 42 may be any devices suitable for storing data, such as a collection of hard disk drives or other integrated non-volatile memory. The storage devices 42 may be SCSI devices, or Fibre Channel devices, for example. Each storage device is

coupled to a storage controller 44. Storage controller 44 is a device suitable for coordinating access to storage devices 42. Storage controller 44 may be a RAID (Redundant Array of Independent Disks) controller whereby storage devices 42 can be grouped into RAID volumes. Each storage device 42 or RAID volume may be assigned a logical unit number (LUN) address. Hosts 32 within server network 30 can transfer data between other servers 32 as well as to and from storage subsystem 40. Storage subsystem 40 provides a large amount of storage space and can be operated as the consolidated storage for computer network 28. Storage subsystem 40 can include fewer or more storage devices 42 than depicted in Figure 3.

Computer network 28 may also include dedicated backup storage devices 46 that are coupled to fabric 36. Dedicated backup storage devices 46 can include, for example, computing devices having removable storage such as a tape medium or any other computer readable medium conventionally used for backup storage. For example, the dedicated backup storage device 28 can include a tape storage device such as a DLT tape library. Dedicated backup storage devices 46 can provide backup services to storage subsystem 40. Computer system 28 also includes a name server 48 that is coupled to the fabric 36. The name server 48 is operable to provide, in response to a name server query, a list of network devices on the fabric 36. For example, the name server 48 may maintain a database of all devices that perform a fabric login to fabric 36. The name server 48 may be a function provided by the fabric switches 38.

Figure 4 shows the HBA port login process during storage assignment. Storage assignment is the process of apportioning storage devices to each host. At step 50, a management application queries the fabric 36 for all available target devices from the name server 48 in the fabric 36. Typically, this occurs after the HBA has performed a fabric login. The management application is any software agent that allows the user to manage target device allocation to the hosts. For example, the management application allows the user to allocate storage devices to the hosts. The management application communicates between the end user and the HBA driver to allow the user to allocate the target devices. The management application can be centralized or distributed. The management application may include, for example, storage consolidation software that allows storage to be shared or apportioned among servers, implement LUN masking to prevent the operating system from

automatically assigning LUNs, and provide other functions to manage a network environment. In response to the management application's query, the name server 48 provides a list of the unique hardware addresses for all the target devices in the fabric 36. As discussed above, name server 48 is a server that maintains a list of all the target devices, such as storage devices 42, in the fabric 36. Name server 48 also maintains a list of all the corresponding unique hardware addresses for the target devices in the fabric 36.

The unique hardware address is a hardware specific label or address that is unique to each node of a network. For example, the unique hardware address may be a port name or a node name. Thus, each storage device 42 has a globally unique hardware address for its network connection. A unique hardware address may be similar to a media access control (MAC) address, an hardware addressing system implemented by the Institute of Electrical and Electronics Engineers, Inc. (IEEE). The unique hardware address may be any globally unique assigned number referenced or maintained according to a standard. For Fibre Channel networks, the unique hardware address is preferably a World Wide Name (WWN). Other types of unique hardware addresses may be used with other types of network protocols. A WWN is a unique number assigned by a recognized naming authority, such as IEEE, that identifies a connection or a set of connections to the network. WWNs are often assigned via a block assignment to a manufacturer of network hardware. A WWN is assigned for the life of a connection (for the device). Most networking technologies, such as Ethernet, FDDI and others, use a worldwide naming convention. The management application can retrieve a list of the target devices on the computer network 28 from the fabric 36 via name server query commands such as get node name (GNN\_ID) and get port name (GPN\_ID). These commands identify the node name and port name for each target device on the computer network 28. Thus, these commands provide the HBA with the WWN information from the Fabric name server 48 for each target device on the network 28. The name server 48 is able to provide a list of all target devices on the fabric 36, because each device on the network 28, such as an HBA or storage device 42, must perform a fabric login, or FLOGI, with the fabric 36 at initialization time. Each network device provides the WWN information associated with its port during the fabric login process, which is initiated by the network device.

At step 52, the user or system administrator selects the target devices that will be assigned to the hosts 32 from the list of unique hardware addresses provided by the management software. For example, the user may select and assign a storage device 42 to a host 32 for the purposes of data storage allocation. At step 54, the management application  
5 passes the selection of target devices that the host 32 may access to the HBA driver associated with the host 32. The HBA driver then stores the unique hardware addresses of the selected target devices on a unique hardware address access list or table associated with the HBA driver in step 56. The unique hardware address access list may be stored in a memory location that may be accessed by the HBA. For example, the unique hardware  
10 address access list may be stored in the HBA's memory. The HBA driver then performs port logins with only those target devices whose unique hardware addresses are present on the unique hardware address access list at step 58. Next, the user performs a device rescan so that the upper driver, such as a SCSI driver, may discover the new target devices at step 60. Thus, each HBA on each host 32 is not permitted to perform a port login with a target device  
15 at initialization, unless the user or system administrator, through the management application, has configured the host 32 or HBA to do so. The management application allows the user or system administrator to select a target device based on the unique hardware address of the target device and then authorize the HBA to perform a port login with that target device. The user may also de-select target devices from the unique hardware address access list. The  
20 management application allows the user to de-select the device and passes this information to the HBA driver. The HBA driver then performs a port log-out of the de-selected device.

Figure 5 shows the HBA port login process during device discovery. Device discovery is the process of determining what devices are connected to the fabric 36 in order to determine the extent and availability of network resources. At step 62, the HBA driver  
25 queries the fabric 36 for available target devices from the name server 48. The name server 48 returns a name server in response to the HBA driver's query. The name server list is a list of the unique hardware addresses of all the target devices connected to the fabric 36. Next, the HBA driver reviews the name server list. At step 64, the HBA driver compares each target device on the name server list to the unique hardware address access table. For each  
30 target device on the name server list, the HBA driver determines whether or not that target

device is included on the unique hardware address access table. at step 66. If the, target device is not listed on the unique hardware address access table, then this absence indicates that the host 32 associated with the HBA driver is not entitled to have access to that target device. Accordingly, the HBA driver continues to the next entry on the name server list and  
5 compares the next target device to the unique hardware address access table as shown in step 64. However, if the target device listed on the name server list is also on the unique hardware address access list, then this indicates that the host 32 associated with the HBA driver is entitled to have access to that target device. Accordingly, the HBA driver performs a port login with the target device in step 68. If there are more target devices listed on the name  
10 server list, then the HBA driver continues to the next target device listed on the name server list to determine whether this target device is also listed on the unique hardware address access list. Thus, the HBA driver repeats steps 64 through 68. If there are no more target devices listed on the name server list, then the HBA driver has made a determination for every target device connected to the fabric 36. After the HBA driver has loaded and  
15 completed its comparison of the unique hardware address access list with the name server list, other drivers and software of a higher level functionality are loaded. Other drivers that may be loaded include those drivers necessary for the host 32 to read off its hard disk drive, run the video cards, display signals on the monitor, initialize the start menu, and other basic functions. At step 72, the upper driver, e.g. the SCSI driver, discovers all the target devices  
20 with which the HBA driver has logged-in.

Note that the LUN masking driver is a higher level functionality than the HBA driver and therefore loads onto the host after the HBA driver. Because the unique hardware address access list preferably lists only those target devices to which the host 30 should have access, the LUN masking driver will not need to mask any of the target devices listed on the  
25 unique hardware address access list. When the operating system initially loads onto the host 30, the operating system will communicate with the disk driver to identify the target devices that are located on the computer network 28. Accordingly, the operating system issues a command to identify all of the available LUNs on the computer network 28. The disk driver will respond with all of the LUN addresses that are not masked. The LUN masking driver  
30 effectively prevents the corruption of target devices such as storage devices 42 by masking

the existence of the storage devices 42 from the operating system. The operating system will only be able to view, and accordingly access, those LUNs that are not masked.

The presently disclosed system and method alleviates the problem of unnecessary HBA port logins. Because the HBA will only perform a port login with a selected target device, rather than with every target device identified on the fabric 36, the number of port logins that a target device can support does not serve as a limitation to the expansion of the computer network. Managing the HBA port logins does not restrict the flexibility of the computer network 28 because the hosts 32 do not need to have access to every target device on the fabric 36. For example, target devices such as storage devices have inherent limitations in terms of performance bottlenecks and storage capacity that prevent the target device from effectively serving a large number of hosts 32. In fact, it is preferable that each host 32 only have access to only a selected set of storage devices, for example, in order to avoid the risk of data corruption as discussed above.

Although the disclosed embodiments have been described in detail, it should be understood that various changes, substitutions, and alterations can be made to the embodiments without departing from their spirited scope.